



## Portable Power Hub

#PH125

www.projecta.com.au



### DESCRIPTION

Power-Hub turns your battery into a versatile user friendly option for powering and charging a wide range of accessories and appliances while you are 'off the grid'. It is the ideal alternative to a conventional dual battery system, giving you the freedom to take power away from your vehicle.

Features 10 power outlets and a 300W inverter

### FEATURES

- 2.4" colour LCD monitor utilises patented 'self-learning' technology to provide comprehensive battery status information
- 300 Watt pure sine wave inverter for powering sensitive electrical equipment
- Compatible with a wide range of battery sizes and chemistry tapes. Simply fit the chosen battery and you're good to go
- Includes: 2A merit socket, cigarette lighter, engel type socket, heavy duty 50A socket, DC terminals & AC outlet with on/off switch

### TECHNICAL SPECIFICATIONS

<b>Suitable Batteries</b>	• Batteries up to N70
<b>Battery Size</b>	• Deep cycle: 60-140 AH • Automotive: 300 - 800 CCA • Marine: 350 - 950 MCA
<b>Battery Compartment</b>	• 338mm L x 177mm W x 230mm H
<b>External Size</b>	• 390mm L x 235mm W x 337mm H
<b>Outlets</b>	• 2 x 15A merit    • 1 x DC terminal • 2 x 2A USB     • 1 x 50A heavy duty • 1 x 10A engel   • 2 x 10A cigarette socket • 1 x 240V AC outlet with on/off switch
<b>Screen</b>	• 2.4" colour LCD
<b>Low Battery Alarm</b>	• Configurable
<b>Material</b>	• Glass reinforced plastic

### Suitable Battery Models

Brand	Model	Capacity (Ah)
Atlas	• DC31MF	• 100 Ah
	• N70T	• 100 Ah
Century	• C12-105DA	• 103 Ah
	• C12-120DA	• 123 Ah
Exide	• LCS31-110	• 110 Ah
	• LCS27-110	• 110 Ah
DEKA	• LCG31-120	• 120 Ah
	• 8A31DTM	• 105 Ah
Full River	• DC105-12	• 105 Ah
	• DC120-12	• 120 Ah
Ultimate	• UL00-VO	• 100 Ah
	• UL110	• 110 Ah
Remco	• RM12-100	• 100 Ah
Ritar	• RA12-100SD	• 100 Ah
	• RA12-120SD	• 120 Ah