

RV POWER OPERATING DEVICE



RV Power Operating Device

#RVPOD

www.dascosupplygroup.com.au

DESCRIPTION


Custom developed for the Caravan industry, the POD allows you to safely and legally connect your caravan to a domestic 10 amp outlet without the fear of overloading or causing damage to your home power supply and appliances.

Manufactured to be used outside, this product features IP66 water protection, RCD safety switch and MCB overload protection.

- Connects safely and legally from 15 Amp RV to domestic 240V 10 Amp outlet
- Suit up to 10mm thickness power cord cables
- Inbuilt circuit breaker for added overload protection
- Residual current device for further protection
- Waterproof ingress protection rating of IP66
- Fluorescent yellow finish for high visibility
- 1 year warranty



Hanging hook for use in vertical position



Suit up to 10mm thickness



IP66 waterproof ingress protection

TECHNICAL SPECIFICATIONS

Lead Length	• 1.5 meter lead
Voltage	• 220 - 250 V AC
Input Amperage	• 10 Amp – pre-wired power cable
Output Amperage	• 15 Amp – external power cable
Plug Type (Input/Output)	• 3 flat pin plug
Approvals	• AS/NZS 3190:2011
Body Colour	• Fluorescent yellow
Ingress Protection Rating	• IP66 rated (when sockets are connected correctly)
Circuit Safety	• Weather seal • Combined 10A circuit breaker and 30MA RCD

